

### Manufactured in the U.S.A.



"Lighting for the Professional Designer"

### PRODUCT Construction

Applications: Building Exteriors and Interiors

Voltage: Line Voltage (120V) System (12V Optional)

Socket Base: Medium Base Sockets are Permanently Attached in

Parallel Wiring

Lamps: Replaceable LEDs (50,000Hrs Lamp Life) are

protected with Shatterproof, Sealed Globes (LEDs Included). Available with Incandescent Line Voltage

(120V) or Low Voltage Lamps (12V)

Spacing: 6", 12", 24", 36", 48", 60" or other Custom Spacing Length: Built to Order (Custom Lengths to Fit Application) Lead Wire: Standard 6' lengths (Custom Lengths Available)

Mounting: Surface Mount or Suspended

Options: Mesh Canopies with Custom Finishes Canopies and Cages with Custom Finishes

# ELECTRICAL information

MarketLite is a LINE VOLTAGE (120V) system that can carry up to 1800 Watts in a single run (20 amp - 12 gauge wire). MarketLite is available with low voltage lamps (12V) which will require a 12 volt (secondary side) transformer. Our standard transformers' primary side voltage are 120 or 277 volts. Consult factory for other voltages.

### CALIFORNIA ACCENT LIGHTING, INC

## APPLICATION information

MarketLite is a LINE VOLTAGE (120V) system available with long life, energy efficient LEDs. MarketLite can be installed using the special hooks on the lamp sockets to an aircraft cable. MarketLite can be field cut for an easy and fast installation not requiring exact field dimensions.

MarketLite is excellent to illuminate areas for accent or decorative lighting. MarketLite creates a warm, pleasant environment in outdoor venues, restaurant interiors, patios and other applications.



ETL Listed Dry or Wet Location Meets UL and CSA Requirements Lighting Facts Partner LM79 Testing Available



